

wireless  
communication  
devices



**APCX**  
EVENTS

# BOLERO WIRELESS INTERCOM INTEGRATED / STANDALONE LINK / STANDALONE 2110 (AES67)



## Bolero Active Antenna - 2.4GHz

- Up to 250 Beltpacks and 100 antennas per Bolero Net
- Intelligent use of bandwidth results in 8 Beltpacks per antenna
- Decentralized SMPTE 2110-30 (AES67) IP-networked antennas
- Fully re-programmable FPGA to handle future networks



# Hollyland Solidcom M1 8B



- Base Station: PoE/LAN (RJ45), Power Supply (RJ45), 4-wire audio (RJ45), 2-wire audio (XLR 3-pin), USB
- Beltpack: 3.5mm Headset, LEMO headset, USB Type-C
- Frequency Response: 200Hz – 7kHz
- Signal to Noise Ratio: >50dB
- Distortion: less than %1
- Frequency Band: 1.9GHz
- Modulation Mode: GFSK
- Transmit Power: Max. 21dBm
- Maximum Range: 450 meters line-of-sight
- Receiving Sensitivity:  $\leq -93$ dBm



# Hollyland Solidcom S1 Pro



- Hollyland Solidcom s1 Pro-8S Full-Duplex ENC Wireless Intercom System with 8 Headsets (1.9 GHz)
- Master Headset
- 8 x Follower Headset
- Charging Case
- 8 x Over-Ear Leather Cushion
- 8 x On-Ear Foam Cushion
- 8 x Mic Windscreen
- 12 x Battery
- USB Type-A to USB Type-C Cable
- Power Adapter



# Hytera PNC380 Zello Walkie Talkie 4G network SIM card IP67 waterproof wireless Two Way Radio



LTE

Asia,Europe,Middle East and Africa: TDD-LTE: B38/B39/B40/B41; FDD-LTE: B1/B3/B5/B7/B8/B18/B19/B20/B26/B27/B28; American: TDD-LTE: B38/B41; FDD-LTE: B2/B3/B4/B5/B7/B12/B13/B17/B26/B28

CDMA

Asia,Europe,Middle East and Africa:BC0  
Asia,Europe,Middle East and Africa:B1/B3/B5/B8; American:B2/B4/B5

WCDMA

Asia,Europe,Middle East and Africa:BC0

TD-SCDMA

Asia,Europe,Middle East and Africa:B34/B39

GSM

Asia,Europe,Middle East and Africa:1900/1800/900/850; American:1900/1800/900/850

WLAN

2.4GHz and 5GHz

NFC

PNC380 Pro : Supported(optional)

BT

BT 4.1

Positioning

GPS/GLONASS/BDS/AGPS

# TH-UV8000D

## TYT VHF/UHF Handheld Walkie talkie Radio



### Specifications:

- Frequency range: VHF: 174~136MHz, UHF: 520~400MHz
- Frequency stability:  $\pm$ . 5 ppm
- Operating voltage: DC 7.2V (rechargeable lithium-ion battery)
- Antenna impedance: 50 ohms
- Operating mode: single or half duplex
- Battery capacity: 3600 mAh
- Dimensions (without antenna): 4,5×3,6×13,5 cm

### Features:

- 10W high-power cross-band repeater function
- Dual range, dual display, dual standby
- 2 x 128 channel storage
- FM radio receiver and 25 channels
- Frequency interval (12.5 / 25 kHz)
- Hands-free talk (vox) function
- CTCSS/DCS encoding
- Supports groups
- Low battery alarm/emergency alarm/transmitter repeater function
- DTMF and turn off or disable the remote control function
- Selectable tri-color background
- Tone 1750 Hz
- Channel search
- Job monitoring
- (TOT)

# Tour Guide Microphone and Headsets



- 1 transmitter
- 1 x 16-slot charging base  
( US/EU/UK plugs available)
- 2 x headset microphone

4 h fully charged, transmitter works for 18 h, receiver works for 100-80 h  
2.4Ghz international public frequency band  
Working range 150 m/492 ft  
Built-in microphone in the transmitter  
Noise reduction and excellent audio quality  
999 channel IDs



The logo for Apex Events is centered on the left side of the image. It consists of a white circle with a yellow ring around it, all set against a dark grey background. Inside the white circle, the words "APEX" and "EVENTS" are written in a bold, black, sans-serif font. The letter "E" in "APEX" has a small orange triangle on its top right corner.

**APEX  
EVENTS**

**thank  
you**

Zone 54, Al Waab Street NO: 625, Building NO: 120  
Office NO: F05 & F06 Sport Accelerator, Aspire Zone

M: +974 3383 4548, +974 77716660, T : +974 4412 0030, F : +974 4412 0330

events@apexqatar.com | www.apexqatar.com